

666E-LX

qunda
Controller
Expert

qunda Controller Expert
KT-3999
**UNIVERSAL A/C
REMOTE**

- 4000 IN 1
- Codes inputting
- Timer on/off
- Clock function

4000
in 1

UNIVERSAL A/C
REMOTE

- 4000 IN 1
- Codes inputting
- Timer on/off
- Clock function



Name: QUNDA Technology (Jiangsu) Co., Ltd.
Address: NO.888 Longqiao road, wujiang economy
development area, Suzhou, Jiangsu, China
Post code: 215200
Web site: www.qunda.com



Product Description

KT-3999 is a universal remote with 4000 codes which is suitable for domestic/international kits, new/old models, constant frequency/inverter units, and can control 98% air conditioner all over the world. It contains timer on/off, digital keys input. Due to digital keys inputting which is our patent (patent NO. ZL200610023186.7), even thousands codes, we only few seconds to finish the setting. So it is your best choice to update and replace the original remote. Please carefully read the instruction before setting to help you use it easily.

Main brand list

ALPIN	HUAKE	SAMPO
AUCMA	HUAMEI	SAMSUNG
AUX	HUALING	SANYO
BANSHEN	HUIFENG	SASUKI
BOERKA	HUIKANG	SHANGHAI
CARRIER	HYUNDAI	SHANGHONG
CHANGHONG	JDC	SHARP
CHIGO	JANGNAN	SHENFENG
CHOFU	JINTAR	SHINCO
CHUNLAN	JINSONG	SHUANGLU
CORONA	JOHNSON	SHUAIKANG
CONROWA	KANGLI	SONGGE
CONSUL	KELON	SOVA
DAEWOO	KUMATAIR	SUMMER
DAIKIN	KOLIN	SUNDURG
DOCTOR	KONKA	SWAN
DONGBAO	LG	TADIRAN
DONGXINBAO	LIANGYU	TATUNG
ELECTROLUX	LITLEDUCK	TCL
FEDDERS	LOREN-SEBO	TECO
FRESTECH	MACQUAY	TIANDI
FUJITSU	MICOM	TOSHIBA
FUNAI	MIDEA	TRANE
GALANZ	MITSUBISHI	UNI-AIR
GENERAL	NORITZ	WANBAO
GUOQIAO	National	PANASONIC
GLEE	PANDA	WHIRLPOOL
GOLDSTAR	PHILCO	XIENG
GREE	PROTON	XINLE
HAIER	RAYBO	YANGZI(YAIR)
HISENSE	ROWA	YINIAN
HITACHI	SABRO	YORK
HUABAO	SAJU DENKI	ZHEN BAO

MADE IN CHINA
NO. B-E-00027

666E-LX



KT-3999 Universal A/C remote user guide



Product Description

Dear User:
Thanks for choosing QUNDA remote. Bring you more convenience is our best wish. KT-3999 is a universal remote with 4000 codes which is suitable for domestic/international kits, new/old models, constant frequency/inverter units, and can control 98% air conditioner all over the world. It contains timer on/off, digital keys input. Due to digital keys inputting which is our patent (patent NO. ZL200610023186.7), even thousands codes, we only few seconds to finish the setting. So it is your best choice to update and replace the original remote. Please carefully read the instruction before setting to help you use it easily.

Preparation

The remote control can be used after setting. Open the cover of battery, put 2 AAA (VM-4, R03) batteries as per polar indicated on the battery cabin.

Patent coding set up

1. Find out the codes that required from the code table. There are many groups' codes of each brand. Please try the first group, if it does not operate your device, try the second, and do like this until the codes can operate your equipment. Ex: AUCMA, you can choose 0288, if it does not work, please try the 0289etc.
2. Press the SEL button for 1 second and release, the code on the LCD blinks once. Enter the 4 digit code in turn. Ex: 0288, press the "0" button, "0" stop blinking, the last three number blinking, then press the "2" button, the last two number blinking, and press the "8" button, the last number blinking, finally press the last number "8", all of the 4 digit code "0288" stop blinking, code entry is complete now. The remote control confirm the code automatically, and then these numeric button get back original function normally. You can operate your air conditioner now.
3. After your air conditioner on, try the other functions of your equipment. If do not operate your device. Please choose the next group of code until all the functions can work. The remote control is 4000 codes in one, so it is invalid when the code greater than 4000.

Auto-search by one key

- If you do not know the brand of your air conditioner, or if your brand is not listed in the code cable, try searching for your code as follow:
1. Put the remote control aim at your air conditioner, press the "SEL" button for 5 seconds and release, the remote control is entering the auto-search status, launch the signal continuously, the code blinking and increasing. When the air conditioner receive the signal, and send a BUZZER, press any keys to confirm.
 2. After your air conditioner on, try the other functions of your equipment, if do not work, repeat these steps until it can operate your equipment.

Clock set up

1. Press the "CLOCK" button, clock signal is blinking.
2. Press the "TIME+" "TIME-" of the time button, setting to the current time.
3. Press the "CLOCK" button again, stop blinking, the time setting is complete. (If you did not press the "clock" button, it can be setting automatically after 5 seconds)

TIMER ON

- You can set timer on, only turning off your air conditioner.
1. Press the "ON" button, the LCD displays the clock signal "0:00" and time blinking.
 2. Press "TIME+" "TIME-" button, adjust the time when you want to make the air conditioner turn on automatically.
 3. Time blinking and it will stop after 5 seconds. The LCD displays current "0:00" time and clock signal. Now setting is complete.

TIMER OFF

- You can set timer on, only after turning on your air conditioner.
1. Press the "OFF" button, the LCD displays the clock signal "0:00" and time blinking.
 2. Press the "TIME+" or "TIME-" button; adjust the time when you want to make the air conditioner turn off automatically.
 3. Time blinking, and it will stop after 5 seconds. The LCD displays current time "0:00" and clock signal. Now setting is complete.

Note

1. If you press TIMER ON/OFF twice continuously, timer is deleted.
2. After timer setting is finished, you should make the remote control's emit directs to your air conditioner's receiving location in available distance. If not, the settings deleted.
3. If you want to see the timer, you should press the TIMER ON/OFF key, the LCD will display the time and after 5 seconds it will display current time.

Attention

1. If it is not used for a long time, remove the battery to avoid leakage liquid of the battery to damage the machine. When the LCD looks dim, please change batteries. (New and old batteries can not be used together) After the batteries are replaced every time, it is not necessary to set model code again.
2. As usual the LCD only display the time when pressing model codes "Enter" button, you can find the code and it is showed on LCD. After 5 seconds it returns time.
3. Check carefully that there is no remora between remote controller and Air conditioner when the time on/off doesn't work. Because the operation is effective only when the air conditioner receives the time on/off signal from remote controller.
4. The manufacturer keeps the right to change the parameter and function of product.

Technical Parameters

Controllable distance: Large than 8 meters
Power supply voltage: DC3V
Battery model: Battery AAA(UM-4, R03) *2
Dimension: L123mm * W44mm * D22mm
Weight: Approx. 45g(text, the batteries)

Manufacturer

Name: QUNDA Technology (Jiangsu) Co., Ltd.
Address: NO.888 Longqiao road, wujiang economy
development area, Suzhou, Jiangsu, China
Post code: 215200 Web site: www.qunda.com

★ The final explanatory right is reserved this company. Any alteration on the design and model will not be further notified.



KT-3999 Universal A/C remote user guide



Brand	Model Code
ALPIN	0252, 0253, 1788, 3325
AUCMA	0288-0296, 0462, 2337, 3534
AUX	0297-0300, 0451, 0474, 0475, 2860, 3370
BANSHEN	0264, 1288, 3848
BOERKA	0383, 0434, 0436, 0437, 3967
CARRIER	0203-0209, 0456-0458, 0482-0486, 0563-0565
CHANGHONG	0301-0308, 1325, 2353, 3982
CHIGAO	0379-0382, 0489, 0515, 1916, 2940
CHOFU	0184-0187, 1721, 3771
CHUNLAN	0345-0350, 0450, 0453, 3932
CORONA	0155-0163, 0459, 2206
CONROWA	0377, 1913, 3997
CONSUL	0463, 0975, 2511
DAEWOO	0203-0209, 0406, 2256, 3990
DAIKIN	0171-0183, 0566, 0577, 2220, 3758
DOCTOR	0221, 0449, 2497, 3850
DONGBAO	0355-0361, 2403, 3430
DONGXINBAO	0413, 2461, 3997
Electrolux	0216-0220, 0569, 1753, 3802
FEDDERS	0498, 0499, 0528
FRESTECH	0277, 0519, 0520, 1813, 3349
FUJITSU	0127-0137, 0464, 0652-0654, 1168, 3720
FUNAI	0430, 0481, 1966, 3502
GALANZ	0371, 0372, 0521, 1395, 2933, 3956
GENERAL	0639, 1152, 2180, 3711

Brand	Model Code
GLEE	0398, 0399, 2446, 3983
GOLDSTAR	0201, 0466-0469, 2515
GREE	0309-0316, 0482, 0512, 0513
HAIER	0266-0272, 0453-0455, 3852
HISENSE	0332-0335, 0517, 1869, 2895, 3917
HITACHI	0118-0126, 1148, 2679, 3709
HUABAO	0336-0344, 1879, 3409, 3926
HUAKE	0408, 1432, 2765, 3992
HUAMEI	0402, 0460-0465, 1997, 3533
HUALING	0317-0325, 0452, 2500, 3906
HUIFENG	0370, 0882, 2420, 3954
HUIKANG	0368, 0441-0443, 2416, 3514
HYUNDAI	0202, 0433, 0480, 1226, 2250
JDC	0373, 0440, 1397, 3000
JINDA	0414, 1950, 2536
JINSONG	0389-0391, 0446-0448, 3462
JOHNSON	0245, 0492, 2028, 3829
KANGLI	0374, 0375, 2935, 3958
KELON	0282-0287, 0473, 0485-0488
KUMATAIR	0225, 0226, 0452, 1988, 3810
KOLIN	0416-0418, 1952, 2465, 3539
KONKA	0397, 0457-0459, 2507, 3981
LG	0197-0200, 0514, 2050, 3730
LIANGYU	0233, 0451, 1257, 3523
LITTLE DUCK	0527, 0532, 1556, 2070

Brand	Model Code
LOREN-SEBO	0255, 0471, 0472, 1496, 3543
MACQUAY	0234-0237, 0465, 2283, 3820
MICOM	0415, 1439, 2463
MIDEA	0260-0265, 0526, 1284, 2310
MITSUBISHI	0001-0045, 0476-0479, 0522, 0523, 0568, 0582, 3628
NORITZ	0431, 1455, 2468
PANASONIC National	0138-0154, 0483, 0490-0492, 2019, 3738
PANDA	0378, 0890, 1405
PHILCO	0210, 0211, 0487, 0488, 3795
PROTON	0421-0423, 2507, 3593
RAYBO	0362-0367, 1387, 2925
ROWA	0369, 0438, 0439, 0494, 0527, 0531, 1975, 3510
Sabro	0435, 0506-0508, 2483, 3579
SAJU DENKI	0212-0215, 1238, 3285
SAMPO	0424-0426, 1448, 3497
SAMSUNG	0188-0196, 0516, 0518, 2239, 3772
SANYO	0048-0095, 0559, 0529, 0530, 1090, 3678
SASUKI	0254, 0470, 2006, 3838
SHANGLING	0384-0388, 0444, 0445, 3969
SHARP	0096-0106, 0525, 1633, 2150, 2656
SHINCO	0351-0354, 0454-0456, 2912
SHUANGLU	0376, 0404-0407, 0480, 3478
SHUAIKANG	0288, 0800, 1311
SONGGE	0428, 0429, 1965, 2988

Brand	Model Code
SOVA	0409, 0410, 2457, 3482
SUMMER	0427, 1963, 2458, 3499
SUNDURG	0257, 0505, 1793, 3841
SWAN	0434, 0477, 0516, 0524, 0946, 1556
TADIRAN	0246-0251, 2295, 3833
TATUNG	0419, 0420, 1955, 2979
TCL	0273-0281, 0476, 0493, 0570, 1299, 3347
TECO	0256, 0473-0475, 1280
TIANDI	0415, 0927, 1538, 3999
TOSHIBA	0107-0117, 0479, 0561, 0562, 1647, 3161
TRANE	0227-0232, 0739, 2276
UNI-AIR	0222-0224, 0450, 3522
WEILI	0393-0396, 2442, 3979
Whirlpool	0164-0170, 0502, 2038, 3752
WINIA	0481, 0550, 1505, 3553
XILENG	0411, 0412, 2460, 3995
XINLE	0400, 0401, 2960, 3985
YANGZI(YAIR)	0403, 1427, 3475
YINYAN	0258, 0259, 0326-0331, 0478, 2888
YORK	0107, 0238-0243, 0573, 2287, 3312
Zhen bao	0639, 1164, 2176, 3200